

ICS 2022 Problem Sheet #7

Problem 7.1: *quine-mccluskey algorithm*

(4+4+2 = 10 points)

A Boolean function F is defined using the following sum of minterms:

$$F(A, B, C, D, E) = m_0 + m_2 + m_4 + m_6 + m_9 + m_{10} + m_{13} + m_{14} + m_{15} + m_{16} + m_{17} + m_{21} + m_{26} + m_{28} + m_{30} + m_{31}$$

- a) Calculate the prime implicants of F .
- b) Construct the prime implicant chart and identify the essential prime implicants.
- c) Write out all minimal boolean expressions defining F using the mathematical logic notation.